



ARINC 600 Size 1 Socket Contact

for UH22089





Mounting Instructions ARINC Rack Connector (Rear) Coax Connector Mounting Block Locating Sleeve Screws & Lockwashers included (4 each)

PERFORMANCE

Nominal Impedance: 50 Ohms

Frequency Range: 0 - 5 GHz

Voltage Rating: 1000 V(rms)

Insulation Resistance: 5000 Megohms min.

CONNECTOR WEIGHT (Each)

1.51 ounces (42.87 grams)

RoHS COMPLIANT

Complies to RoHS Standards

INSTALLATION

Center Contact

Solder Only

Crimp Ferrule

M22520 / 5-01 Tool M22520 / 5-25 Die Set (.429" A hex)

CONSTRUCTION

Materials:

Body Brass, ASTM-B16,

Alloy UNS 36000, H02

Center Contact Beryllium Copper, ASTM-B196,

Alloy UNS C17300

Ferrule Tellurium Copper, ASTM-B301,

C14500, H02

Or D.H.P Copper CDA, Alloy 122, Temper Hard

Dielectric TFE Fluorocarbon, ASTM-D1710,

Type 1, Grade 1

Spring, Retaining Ring Stainless Steel

Mounting Block Aluminum, Alloy 6061 T6

Finish:

Body, Ferrule Gold
Center Contact Gold
Spring, Retaining Ring Passivated
Mounting Block Iridite

APPLICABLE STANDARDS

ARINC 600

Notes :

 A 2.0" piece of Raychem ATUM heat shrink P/N ATUM-16/4-0 provided with connector for purpose of strain relief & moisture protection.

2) Please refer to T-1504XX Termination Instruction sheet for strip dimensions & instructions.